

# CSAT-5060 & CSAT-6070 C-Band Transceivers

Transceivers



5 to 25 W P1db  
(6 to 32 W Psat)



50 W P1db  
(63 W Psat)



100 & 125 W P1db  
(125 & 150 W Psat)

## Introduction

The CSAT-5060 and CSAT-6070 C-Band Transceivers provide superior performance, long-term reliability, and ease of installation. A very price-competitive product, these transceivers embody the best design efforts of our highly experienced RF engineering team.

## Full Rated Power

The CSAT-5060 and CSAT-6070 deliver the full rated power, or more, measured at the 1 dB compression point and at the output flange. You will know the useable output power you are paying for, and receive full value for your investment.

## Phase Noise

The dual synthesizers in this family of transceivers deliver superior phase noise performance, exceeding Intelsat specifications by a substantial margin. Your applications will benefit from outstanding spectral purity and the ability to operate in multi-carrier environments with less worry.

## Third Order Intercept (TOI)

The design provides a high TOI that allows multi-carrier applications without the issues normally encountered in low power environments. The CSAT-5060 and CSAT-6070 deliver performance usually found only in split converter SSPA systems.

## Small, Compact Design

The transceivers are enclosed in a single unit chassis. This design allows quick, easy installation for all models in this family of transceivers.

## Full Monitor and Control (M&C)

A variety of full monitor and control methods are designed into the CSAT-5060 and CSAT-6070:

- Convenient connection using an optional small, hand-held terminal
- Easy access via EIA-232 or EIA-485 connections or optional Ethernet support (HTML, Telnet, SNMP)
- Remote management via the CDM modem family or the PC-based SatMac proprietary M&C software

## Redundancy

The CSAT-5060 and CSAT-6070 are available in 1:1 redundant configurations.

## 10 dBm Option

This transceiver is designed to mate with an external high power SSPA (Example: Comtech EF Data HPODs) or TWTA to provide even higher output power. This model is only available on the CSAT-5060.

## Typical Users

- Cellular Providers
- Maritime
- Oil & Gas

## Common Applications

- VSAT point-to-point applications  
– TDMA, DAMA, SCPC/MCPC

## Specifications

### Transmit

Frequency RF			
CSAT-5060	5845 to 6425 MHz Standard 6425 to 6725 MHz (Optional Extended) 5850 to 6650 MHz (Optional Wide) 5845 to 6725 MHz (Optional Super Wide)		
CSAT-6070	6725 to 7025 MHz		
Frequency IF			
70 MHz $\pm$ 18 MHz 140 MHz $\pm$ 36 MHz (Optional)			
Output Power		CSAT-5060	CSAT-6070
	P <sub>1dB</sub>	P <sub>1dB</sub>	P <sub>sat</sub> Typical
10 dBm	10 dBm		
5 W	5 W (37 dBm)		
10 W	10 W (40 dBm)	10 W (40 dBm)	41 dBm (12 W)
20 W	20 W (43 dBm)		
25 W	25 W (44 dBm)	25 W (44 dBm)	45 dBm (32 W)
50 W	50 W (47 dBm)	50 W (47 dBm)	48 dBm (63 W)
100 W	100 W (50 dBm)		
125 W	125 W (51 dBm)		
Gain			
10 dBm	25 dB		
5 W	65 dB		
10 W	68 dB		
20 W	71 dB		
25 W	71 dB		
50 W	74 dB		
100 & 125 W	77 dB		
Attenuator Range		25 dB in 0.25 dB steps	
Gain Flatness		$\pm$ 0.75 dB full RF band $\pm$ 0.75 dB per 36 MHz	
Gain Stability		$\pm$ 0.25 dB at constant C $\pm$ 1.00 dB from -40° to +55°C (-40° to 131°F)	
Carrier Mute		-70 dBc	
Inter-Modulation		-28 dBc typical for two carriers each at 6 dB OPBO from rated power (3 dB total OPBO)	
Second Harmonic		-55 dBc	
Spurious		AC line harmonics	-45 dBc
		Carrier related, <500 kHz	-60 dBc
		All other in-band	-65 dBc
AM to PM Conversion		3.0 Degrees at 6 dB OPBO from rated power	
RF Output VSWR		1.25:1	
RF Output Connector		Type N female CPR-137G	
10 dBm, 5 W, 10 W, 20 W, 25 W, 50 W, 100 W & 125 W			
IF Input Impedance		50 $\Omega$	
IF Input VSWR		1.25:1	
IF Input Connector		Type N female	

### Receive

Frequency RF		
CSAT-5060	Converter LNA	3400 to 4200 MHz 3400 to 4200 MHz(std.) 3625 to 4200 MHz (Optional)
CSAT-6070		4500 to 4800 MHz
Frequency IF		
70 MHz $\pm$ 18 MHz 140 MHz $\pm$ 36 MHz (Optional)		
Gain, without LNA		
45 dB		
Gain Flatness, without LNA		
$\pm$ 0.75 dB full RF band $\pm$ 0.75 dB per 36 MHz		
Gain Stability, without LNA		
$\pm$ 0.25 dB constant temperature $\pm$ 1.00 dB -40° to +55°C (-40° to 131°F)		
Output Power, P <sub>1dB</sub>		
+13 dBm		
Two Tone Inter-Modulation		
-50 dBc for two tones at 0 dBm each, 1 MHz apart		
Image Rejection		
-60 dBc		
RF Input VSWR		
1.25:1		
RF Input Connector		
Type N female		
IF Output Impedance		
50 $\Omega$		
IF Output VSWR		
1.25:1		
IF Output Connector		
Type N female		

### Common

Conversion	Dual, no spectral inversion
Frequency Step Size	1.0 and 2.5 MHz automatic
Frequency Stability	1x10 <sup>-9</sup> /day 1x10 <sup>-7</sup> /year 40° to +55°C 1x10 <sup>-8</sup> /Temperature
Attenuation Steps	TX: 0 to 25 dB in 0.25 dB steps RX: 0 to 20 dB in 0.25 dB steps
Phase Noise	100 Hz -66 dBc/Hz 1 kHz -76 dBc/Hz 10 kHz -86 dBc/Hz 100 kHz -96 dBc/Hz
Group Delay	Linear 0.1 ns/MHz Parabolic 0.02 ns/MHz <sup>2</sup> Ripple 1 ns p-p

### Monitor & Control

Methods	Both RS-485 and RS-232 Serial Interface Optional Ethernet support (HTML, Telnet, SNMP) Optional Handheld Controller
Commands	Set TX frequency Set RX frequency Set TX attenuation Set RX attenuation Report TX output power Mute TX Report internal temperature Report power supply voltages Set time Set date
Faults	Up converter functions Down converter functions Up converter synthesizers Down converter synthesizers Internal reference oscillator LNA current fault Over temperature condition

### Environmental

Operating Temperature	-40° to +55°C (-40° to 131°F) Operating
Storage Temperature	-50° to +75°C (-58° to 167°F) Storage
Altitude	15,000 ft, mean sea level
Humidity	0 to 100 Percent, Relative
Ingress Protection	Designed for IP-66 (Dust tight, strong water jets)
Prime Power	90 to 260 VAC standard 47 to 63 Hz standard 48 VDC optional
Dimensions (nominal)	(height x width x depth)
10 dBm	8" x 8" x 11" (20 x 20 x 28 cm)
10 W to 25 W	10.75" x 8" x 11" (27.3 x 20 x 28 cm)
50 W	9.75" x 10" x 23" (24.77 x 25.4 x 58.42 cm)
100 W & 125 W	10" x 12.5" x 26" (25.4 x 31.75 x 66.04 cm)
Weight	
5 W to 25 W	36 lbs (16 kg)
50 W	65 lbs (29 kg)
100 & 125 W	80 lbs (40 kg)
Low Noise Amplifier	Customer defined
RF Power	
CSAT-5060	10 dBm, 5 W, 10 W, 20 W, 25 W, 50 W, 100 W, 125 W
CSAT-6070	10 W, 25 W, 50 W
AC Power	
CSAT-5060	120 W, 150 W, 200 W, 220 W, 250 W, 410 W, 759 W, 850 W
CSAT-6070	200 W, 250 W, 410 W
Steady-State True AC Power Requirement (110 VAC)	



2114 West 7th Street, Tempe, Arizona 85281 USA  
Voice: +1.480.333.2200 • Fax: +1.480.333.2540 • Email: sales@comtechefdata.com

See all of Comtech EF Data's Patents and Patents Pending at <http://patents.comtechefdata.com>

Comtech EF Data reserves the right to change specifications of products described in this document at any time without notice and without obligation to notify any person of such changes. Information in this document may differ from that published in other Comtech EF Data documents. Refer to the website or contact Customer Service for the latest released product information